

Guangzhou Best Electronic Technology Co., Ltd

https://entelechybattery.com/

Office: 5/F, C District, No. 98, Road 9, Pacific Industrial Zone, Xintang Town, Zengcheng District, Guangzhou, China

BST-SPSS series Solar Generator 3000W/5000W

Feature:

- Low frequency, pure sine wave output.
- Wide AC voltage input range, AVR output.
- Built-in EI transformer/toroidal transformer optional.
- LCD real-time display, concise and straight forward.
- AC prior/EC mode/Battery prior selectable.
- 50Hz/60Hz automatic recognition.
- RS232 communication port optional.
- Support diesel/gasoline generator



Specification	n			
Model BST		BST-SPSS 3000W	BST-SPSS 5000W	
Rated Power		3000W	5000W	
Peak power		9000W	15000W	
Battery Voltage		48(51.2)VDC	48(51.2)VDC	
Built-in LIFEPO4 Battery Capacity		51.2V120AH(6144WH) battery	51.2V198AH(10137.6WH) battery	
Description		3000W 12V Low frequency pure sine wave Inverter +12V 50A PWM Solar controller +1*51.2V120AH LiFePO4 battery, Actual battery capacity :120AH	5000W 12V Low frequency pure sine wave Inverter +12V 60A PWM Solar controller +1*51.2V198AH LiFePO4 battery, Actual battery capacity :198AH	
Parameter				
Capacity	Rated power	3000W	5000W	
	Peak power	9000W	15000W	
Input	Battery Input Voltage Range	42V~60V for 48V system		
	AC Input Voltage Range	73VAC~138VAC or 145VAC~275VAC		
	AC Input Frequency Range	45Hz~65Hz(50Hz/60Hz automatic recognition)		
	Efficiency(Battery Mode)	≥90%		
	Output Voltage(Battery Mode)	110VAC±2% or 220VAC±2%		
	Output Frequency(Battery Mode)	50Hz±0.5 or 60Hz±0.5		
	Output Wave(Battery Mode)	Pure Sine Wave		
Output	Efficiency(AC Mode)	>99%		

	utput Voltage(AC Mode) 110VAC±10% or 220VAC±10%			
	Output Frequency(AC Mode)	Tracking Automatically		
	Output waveform distortion(Battery Mode)	≤3%(Linear load)		
AC charger	AC charging current	Max 15A		
	AC charging voltage	Charge Voltage: 28V for 24V system, 56V for 48V system; Float Voltage: 27.6V for 24V system, 55.2V for 48V system		
	AC charging method	Three-stage(constant current, constant voltage, floating charge)		
Battery Type	Customize battery	Charge and discharge parameters of different types of batteries (such as lithium batteries, etc.) can be customized according to user requirements		
	Charging mode	SMART controller		
	Max PV input voltage(at 25°C)	100V		
PWM Solar	PV input voltage range	60~88V	60~88V	
charger	Charge & discharge current	50A	60A	
	Max PV input power	2800W	3360W	
Solar panel	Solar panel standard	6*275W/30V(2S3P)	8*275W/30V(2S4P)	
	Capacity	1*51.2V120AH	1*51.2V198AH	
Inbuilt battery	Battery size(LxWxH)/pcs	1* (500*400*315mm)	1* (750*400*315mm)	
Working	AC prior(01)	Under AC prior mode, device will always use utility source and through regulator to supply loads as well as charge battery(charging current selectable); when utility power is with high/low/serious distortion or other		
Mode(Selecta	EC mode(02)	Under Energy saving mode, device dedects load, when the load is < 10% rated power, device will auto on/off AC output; when the load is > 10%		
Die)	Battery prior(03)	Under Battery prior mode, device will always use battery source to coverter high quality electricity for load; when battery source is failed, device will auto use utility source and through regulator to supply loads.		
	Battery low voltage alarm	22V for 24V system; 44V for 48V system		
	Battery low voltage protection	21V for 24V system; 42V for 48V system		
	Battery high voltage alarm	30V for 24V system; 60V for 48V system		
D	Battery high voltage protection	34V for 24V system; 68V for 48V system		
Protection	Battery high voltage recover	29V for 24V system; 58V for 48V system		
	Overload protection	Automatic protection(battery mode), circuit breaker or fuse (AC mode)		
	·	Automatic protection (battery mode), circuit breaker or fuse (AC mode)		
	Temperature protection	>90°C(Shut down output)		
	A	Normal working condition, buzzer has no alarm sound		
Alarm	В	Buzzer sounds 4 times per second when battery failure, voltage abnormality,		
Tue weeks w Time s	С	When the machine is turned on for the first time, the buzzer will prompt 5		
Transfer Time Display		≤4ms LCD		
Thermal methor	od	Cooling fan in intelligent control		
Communication		RS232(Optional)		
	Operating temperature	-20°C~55°C		
Environment	Storage temperature	-15°C~60°C		
	Noise Elevation	≤55dB 2000m (More than derating)		
	Humidity	0%~95% ,No condensation		
Discrete 1	Dimention, L x W x H(mm)	820*450*720	820*450*720	
Physical	Net weight(kg)(with battery)	115	157	
_	Dimention, L x W x H(mm)	875*500*880	875*500*880	
Packing	Gross weight(kg)(with battery)	140	182	
Note: All spec	Quantity/CTN ifications are subject to charge with	1pcs per wooden case		
Note: All spec	ifications are subject to charge wit	nout prior notice		